

ADS 1015 Mixer Amplifier - 15W rms ac/dc



Features two unbalanced microphone inputs and two auxiliary inputs for background music. Separate MIC1, MIC2, tone and auxiliary volume controls in addition to a master control. For 100V line or low impedance systems. 240Vac/12Vdc.

Technical Specification

Power Output	15W rms
Loudspeaker Outputs	4, 8, 16ohm / 100V
AC Power	240V 50Hz
DC Power	12V
THD at rated power	<1%
Frequency Response	100Hz – 20kHz
Priority Mic Input -	
Other Mic Inputs	3mV / 600ohm
Aux Input	250mV / 50k ohm
Signal/Noise ratio, Mics	>50dB
Signal/Noise ratio, Aux	>50dB
Tone Control	-12dB@10kHz
Dimensions	H83 x W320 x D230 mm
Weight	3.46kg

Product Code : 10-6211-B10